

TEST NO. 3

The above test was again repeated with another Sales Representative gun (Gun #2187 - Doc Ames' gun). Records indicated this gun had been previously fired 850 rounds without a single malfunction. Power Cone test results on this gun were as follows:

	A	B	C
	Dial-a-matic	Power Cone	Power Cone
	Carrier Latch	Carrier Latch	Carrier Latch
	Magazine Flipper	Magazine Flipper	Magazine Flipper
	(Feb. '56)	(Feb. '56)	(Feb. '56)

Malfunctions

100 ROUNDS WINCHESTER MAGNUM LOADS EACH GUN, 30" FULL CHOKE BARREL

Don't feed from mag. (1st latch)	1	1	2
Don't blow back		1	
Fail to lock open		6	
Dropped shell from magazine			1
Totals	1	8	3
% Malfunction Rate	1%	8%	3%

100 ROUNDS WINCHESTER 2-3/4 TRAP LOADS EACH GUN, 26" IMPROVED CYLINDER BARREL

None	0	0	0
% Malfunction Rate	Zero	Zero	Zero

TEST NO. 4

Further testing results on two additional guns secured from production are as follows:

Gun No. 5955 (30" P.C. Bbl.)	Dial-a-matic Carrier Latch Mag. Flipper (340 rds. All types of ammo.) 3/14/56 & 4/6/56	Power Cone Carrier Latch Mag. Flipper (160 rds. All types of ammo.) 4/5/56
---------------------------------	--	---

Malfunction

Failed to connect	1	
Failed to lock open	3	
Failed to feed from mag. (1st latch)	2	1
" " " " (2nd shell)	7	2
Failed to trip carrier latch	1	
Failed to eject		1
Totals	14	4
% Malfunction Rate	4.0%	2.5%